



S3000K 系列
S3000K SERIES

轴承座型号 Housing No.	轴径 Shaft dia d_1 (mm)	基本尺寸 Dimensions (mm)														座重量 Housing Wt (kg)	轴承型号 Bearing No.	紧定套 Adapter Sleeve	定位环 Locating Ring		
		h h12	W	L	a	b	c	m	g H12	f1 H12	f2	d2 H12	d3 H12	v	u				s	规格 Number	数量 QTY
S3024K	110	112	215	150	390	110	40	320	56	8	10.7	113	135	30	36	M24	16.5	23024K	H3024	FR180/10	1
S3026K	115	125	239	160	420	120	45	350	62	8	10.7	118	140	30	36	M24	19.3	23026K	H3026	FR200/10	1
S3028K	125	140	259	170	420	120	45	350	63	9	12.2	128	154	30	36	M24	24.6	23028K	H3028	FR210/10	1
S3030K	135	150	278	175	460	130	45	380	66	9	12.2	138	164	30	36	M24	29	23030K	H3030	FR225/10	1
S3032K	140	150	288	190	470	130	50	390	70	10	13.7	143	173	30	36	M24	37	23032K	H3032	FR240/10	1
S3034K	150	160	320	200	540	160	55	450	77	10	13.7	153	183	36	48	M30	45	23034K	H3034	FR260/10	1
S3036K	160	170	340	210	560	160	55	470	84	10	13.7	163	193	36	48	M30	65	23036K	H3036	FR280/10	1
S3038K	170	170	353	210	560	160	55	470	85	10	13.7	173	203	36	48	M30	67	23038K	H3038	FR290/10	1
S3040K	180	180	373	235	615	170	60	515	92	10	13.7	183	213	36	48	M30	72	23040K	H3040	FR310/10	1
S3044K	200	200	408	255	690	190	70	580	100	11	15.5	203	240	42	50	M36	98	23044K	H3044	FR340/10	1
S3048K	220	210	433	265	720	200	75	610	102	11	15.5	223	260	42	50	M36	110	23048K	H3048	FR360/10	1
S3052K	240	240	485	285	820	220	80	680	114	12	17.3	243	286	52	70	M45	148	23052K	H3052	FR400/10	1
S3056K	260	250	505	295	860	230	80	720	116	12	17.3	263	306	52	70	M45	165	23056K	H3056	FR420/10	1